



ACT-2402 2.4 GHz Digital Dual-Channel Receiver

Features

- The receiver has a built-in high efficiency antenna on the front panel.
- MIPRO's unique control panel equips a graphic OLED, providing a larger field of view without blind angles.
- Up to 12 channels for interference-free operation in one frequency band.
- Dual tuner true diversity receiving ensures long reception distance and eliminates signal drop-out.
- MIPRO Auto Scan and ACT™ function provide the transmitter's frequency with precise and rapid sync to the receiver.
- Effectively avoids RF interference from UHF communication products
- Antenna connector provides bias for MIPRO antenna systems to boost reception distance and signal.
- External AC 100 – 240 V switching power supply to ensure stable operation of the system even under drastic voltage change.
- Pairs with ACT-240H handheld and ACT-240T bodypack transmitter.
- All are designed and made in Taiwan to ensure high quality and value.



Specifications

Channel	Dual
Chassis	EIA standard half-rack (9.5") metal chassis
Display	Graphic OLED
Frequency Range	ISM 2.4 GHz
Preset Channels	12
Receiving Mode	Dual tuner true diversity receiving
Sample Rate	44.1 kHz / 24-bit
Frequency Response	20 Hz – 20 kHz
Latency	< 4.0 ms
Dynamic Range	> 117 dBA
Output Connector	Balanced XLR & Unbalanced Ø 6.3 mm phone jack, -10 to +20 dB adjustable range
Antenna	Built-in, front panel
Power Supply	DC 12 – 15 V. External AC 100 – 240 V switching power supply
Dimensions	210 × 44 × 162 mm (W × H × D)
Weight	Approx. 0.8 kg
Note	Refer to the actual product in the event of product discrepancy